



SensComp, Inc.
 36704 Commerce Rd.
 Livonia, MI 48150
 Telephone: (734) 953-4783
 Fax: (734) 953-4518
 www.senscomp.com

Ceramic Resonator, 420 kHz

SensComp Electronic Component – Ceramic Resonator, 420 kHz

Features

Used in the Series 6500 Sonar Ranging Module and the Smart Sensor Module.
 Accurately Controls 420 kHz Time-Base Generator

Part No.

PID# 607220 – Ceramic Resonator

Specifications

Specifications – Temperature at 25° C

Case Plastic
 Hermetically Sealed

Series Resonant Frequency 420 kHz \pm 0.5%

Shunt Capacitance (Co) 600 of max
 At 1 kHz

Operating Temperature -20° to 80° C

Temperature Stability 30 ppm/°C Max
 (positive TC) over Operating
 Temperature Range

Aging (Time Stability) \pm 0.3% Max
 For 10 years

Dimensions: dimensions are in mm

Specifications

